

DATA SHEET

ITEM NO. 10019386

Mains and system protection in accordance with VDE-AR-N 4105/4110

PowerShield 500 power cabinet

All values in [mm]
Dimensions "blue"
Fastening points "orange"

Internal arrangement and components may differ depending on the variant!

Minimum distances

above	200	The electrical connection between the cabinets must be provided by the customer! When installing parallel connecting cables (several conductors per phase), the usual installation guidelines must be observed, including the same cable length and short-circuit-proof installation!
below	400	
lateral	200	
front	1400	



SCOPE OF DELIVERY

Quantity	Designation
1	Power Shield 500 power cabinet
1	General installation instructions

Quantity	Designation
1	Circuit diagram

Status: April 2025
The text and illustrations correspond to the technical status at the time of printing and are subject to change without notice.
Despite careful editing, all information is provided without guarantee. Liability is excluded.

DATA SHEET

ITEM NO. 10019386

Mains and system protection in accordance with VDE-AR-N 4105/4110

PowerShield 500 power cabinet

TECHNICAL DATA

NOMINAL VALUES	• applicable / - not applicable	
Rated insulation voltage U_i	[VAC]	660
Rated operating voltage U_e	[VAC]	3PH - 230/400
Rated current I_{nA} (at $\cos \phi 0.9$)	[A]	800
Rated current I_{nA} (at $\cos \phi 1$)	[A]	720
Operating frequency f_n	[Hz]	50
Net shape		TN-S
Max. Value of the back-up fuse (gG/gL)	[A]	1000
Max. Apparent power of the generation system	[kVA]	552
Max. Active power of the generation system	[kW]	497
Type of generating system (VDE-AR-N 4105/4110)		Type 2

DOVE SWITCH TEMPORARILY STORED		
Rated current I_n	[A]	800
Utilisation category		AC-21/AC-22 (A+B)
Undervoltage release	[V]	24
Rated limit short-circuit breaking capacity (I_{cu})	[kA]	70
Separation		three-pole
Type		with motorised drive

DOVE SWITCH SUPERORDINATE		
Rated current I_n	[A]	800
Utilisation category		AC-21/AC-22 (A+B)
Undervoltage release	[V]	24
Rated limit short-circuit breaking capacity (I_{cu})	[kA]	70
Separation		three-pole
Type		with motorised drive

Status: April 2025

The text and illustrations correspond to the technical status at the time of printing and are subject to change without notice. Despite careful editing, all information is provided without guarantee. Liability is excluded.

www.enwitec.eu

DATA SHEET

ITEM NO. 10019386

Mains and system protection in accordance with VDE-AR-N 4105/4110

PowerShield 500 power cabinet

TECHNICAL DATA

OVERVOLTAGE PROTECTION		• applicable / - not applicable
Test class according to EN 61643-11 (type)		I+II/BC
Back-up fuse type		NH1 isolator
Max. Back-up fuse	[A]	200
Highest permissible continuous voltage U_{cpv}	[V]	350
For type 1: Lightning impulse current max. I_{imp} 10/350	[kA]	12,5

NETWORK CONNECTION		
Cable entry		
Introduction		over cut-out base
Clamping range (from - to)	[mm]	-
Connection L1, L2, L3, N, PE		
Connection type		Cable lug M10 [#]
Stripping length	[mm]	-
Tightening torque	[Nm]	30 - 35
Cable cross-section (from - to)		
Cu/Al [#]	[mm²]	max. 240

FUSE-SWITCH DISCONNECTOR FOR MAINS		
Fuse link		4 x NH1
Max. Fuse value	[A]	per separator 250

[#] Use bimetal cable lugs when connecting aluminium conductors! Please observe the processing guidelines for aluminium conductors! The standard processing guidelines must be observed! The contact surfaces of the aluminium conductors must be cleaned, brushed and treated with suitable grease. Cable lugs are NOT included in the scope of delivery.

Status: April 2025

The text and illustrations correspond to the technical status at the time of printing and are subject to change without notice. Despite careful editing, all information is provided without guarantee. Liability is excluded.

www.enwitec.eu

DATA SHEET

ITEM NO. 10019386

Mains and system protection in accordance with VDE-AR-N 4105/4110

PowerShield 500 power cabinet

TECHNICAL DATA

CONNECTION PV / LOADS	• applicable / - not applicable	
Cable entry		
Introduction	over cut-out base	
Clamping range (from - to)	[mm]	-
Connection L ₁ , L ₂ , L ₃		
Connection type	Cable lug M10 [#]	
Stripping length	[mm]	-
Tightening torque	[Nm]	30 - 35
Cable cross-section (from - to)		
Cu/Al [#]	[mm ²]	max. 240
Connection N, PE		
Connection type	Cable lug M12 [#]	
Stripping length	[mm]	-
Tightening torque	[Nm]	35 - 40
Cable cross-section (from - to)		
Cu/Al [#]	[mm ²]	max. 240

FUSE-SWITCH DISCONNECTOR FOR MAINS		
Fuse link	5 x NH1	
Max. Fuse value	[A]	per separator 250

[#] Use bimetal cable lugs when connecting aluminium conductors! Please observe the processing guidelines for aluminium conductors!
The standard processing guidelines must be observed! The contact surfaces of the aluminium conductors must be cleaned, brushed and treated with suitable grease. Cable lugs are NOT included in the scope of delivery.

Status: April 2025

The text and illustrations correspond to the technical status at the time of printing and are subject to change without notice. Despite careful editing, all information is provided without guarantee. Liability is excluded.

www.enwitec.eu

DATA SHEET

ITEM NO. 10019386

Mains and system protection in accordance with VDE-AR-N 4105/4110

PowerShield 500 power cabinet

TECHNICAL DATA

COMMUNICATION	• applicable / - not applicable	
Interface	Feedback and circuit-breaker control	
Cable entries		
Introduction	over cut-out base	
Clamping range (from - to)	[mm]	-
Connections		
Connection type	Spring clamp	
Stripping length	[mm]	10 - 12
Tightening torque	[Nm]	-
Cable cross-section (from - to)		
Fine copper wire with ferrule	[mm²]	0,25 - 2,5
Fine-stranded copper	[mm²]	0,25 - 4
Solid or stranded copper wire	[mm²]	0,25 - 4

VOLTAGE TAP		
Fuse link	10 x 38	
Fuse value	[A]	see circuit diagram
Cable entries		
Introduction	over cut-out base	
Clamping range (from - to)	[mm]	-
Connections		
Connection type	Spring clamp	
Stripping length	[mm]	10 - 12
Tightening torque	[Nm]	-
Cable cross-section (from - to)		
Fine copper wire with ferrule	[mm²]	0,25 - 2,5
Fine-stranded copper	[mm²]	0,25 - 4
Solid or stranded copper wire	[mm²]	0,25-4

Status: April 2025

The text and illustrations correspond to the technical status at the time of printing and are subject to change without notice. Despite careful editing, all information is provided without guarantee. Liability is excluded.

www.enwitec.eu

DATA SHEET

ITEM NO. 10019386

Mains and system protection in accordance with VDE-AR-N 4105/4110

PowerShield 500 power cabinet

TECHNICAL DATA

CURRENT CONVERTER	• applicable / - not applicable	
Transducer lugs	[mm]	80 x 10 x 250
Current transformer position	[A]	between the supply line and the higher-level Dome switch
Current transformer	[A]	1000/5
Accuracy class	[A]	0,5
Connections		
Connection type		Spring clamp
Stripping length	[mm]	13 - 15
Tightening torque	[Nm]	-
Cable cross-section (from - to)		
Fine copper wire with ferrule	[mm]	0,5 - 6
Fine-stranded copper	[mm]	0,5 - 10
Solid or stranded copper wire	[mm]	0,5 - 10

GENERAL		
Dimensions WxHxD (without screw connections)	[mm]	2 x 1286 x 1279 x 470
Weight, approx.	[kg]	232
Operating temperature range	[°C]	-25...+35
Temperature - transport/storage (24 hours 70°C)	[°C]	-25...+55
Humidity - condensing permitted		-
Humidity - permissible range	[%]	5...70
max. installation height above N.N.	[m]	2000
Protection class IP (EN 60529)		43
Outdoor suitability (protected area)		•
Protection class (EN 61140)		II
Housing material		Polyester (GRP)
RoHS-compliant (2011/65/EU)		•
Housing colour		RAL 7035
Mounting type		Floor mounting
Closure type		Locking cylinder

Status: April 2025

The text and illustrations correspond to the technical status at the time of printing and are subject to change without notice. Despite careful editing, all information is provided without guarantee. Liability is excluded.

www.enwitec.eu

DATA SHEET

ITEM NO. 10019386

Mains and system protection in accordance with VDE-AR-N 4105/4110

PowerShield 500 power cabinet



Scherwies 2 | 84329 Wurmanssquick
info@enwitec.eu

TECHNICAL DATA

OTHER	- applicable / - not applicable
Customs tariff number	85371098

ACCESSORIES (not included in the scope of delivery)	
Mounting base (500 mm)*	
Buried base*	

* Either a mounting base or a recessed base is essential for installation

Status: April 2025
The text and illustrations correspond to the technical status at the time of printing and are subject to change without notice.
Despite careful editing, all information is provided without guarantee. Liability is excluded.